



SERIES TS 870 • 100 - 1200 AMP AUTOMATIC TRANSFER SWITCHES

COMMERCIAL & INDUSTRIAL

REGAL®



THOMSON POWER SYSTEMS TS 870 AUTOMATIC TRANSFER SWITCHES OFFER THE FOLLOWING:

ENCLOSED CONTACT POWER SWITCHING UNITS

- Fully enclosed silver alloy contacts provide high withstand rating & 100% continuous current rating.
- 3 cycle short circuit current withstand.
- 10 cycle 6X overload current rating
- Completely isolated utility and generator side power switching units.
- Power switching units can incorporate overcurrent protection, allowing cost savings in upstream devices.
- Not damaged if manually switched while in service.

RELIABLE MOTOR-OPERATED TRANSFER MECHANISM

- Heavy duty brushless gearmotor and operating mechanism provide mechanical interlocking (for open transition ATS) and extreme long life.
- Stored Energy: Motor Operators for fast CTTS
- Safe manual operation permits operation under adverse conditions.

SUPERIOR SERVICEABILITY

- All mechanical and control devices are visible and front accessible.
- All control wires and power busses are front-accessible.
- Plug-in TSC 900 Transfer Switch Controller

CONTROL FEATURES

- TSC 900 microprocessor based controller with 7" color touch screen graphical display and programmable inputs/outputs.
- Isolation plug permits disconnecting control circuits from all power sources.

PRODUCT DATA

- Models from 100-1200 Amp continuous current
- Available 2, 3 or 4 pole
- All models 50/60Hz rated
- Voltage range 120-600 VAC
- 3 phase, 3 or 4 wire systems
- Open Transition or Closed Transition ATS
- 1000/1200A offer fast Open Transition transfer, with in-phase monitoring

QUALITY ASSURANCE

- ISO 9001 Registered

SEISMIC CERTIFICATION

TS 870 ATS is certified for installation and operation per the following requirements:

- IBC 2012– Section 13, Occupancy Category IV
- ASCE7-05 Region 3 (minimum SS=200%)

SAFETY STANDARDS

- UL 1008 Automatic Transfer Switches for use in Emergency Systems
- CSA C22.2 No. 178 Automatic Transfer Switches
- NFPA 110 Standard for Emergency and Standby Power Systems

WARRANTY

- 2 year limited warranty included

Thomson Power Systems TS 870 Standard Automatic Transfer Switches employ two mechanically interlocked power switching units with a microprocessor based controller to automatically start a generator and transfer system load to a generator supply in the event of a utility supply failure. System load is then automatically retransferred back to the utility supply following restoration of the utility power source to within normal operating limits. All load transfer sequences are "Open Transition" (i.e. "break-before make") with adjustable neutral position delay to ensure adequate voltage decay for preventing out of phase transfers.

TS 870 Automatic Transfer Switches are certified to UL 1008 & CSA 178 Standards for use in Emergency Power System applications.

All TS 870 transfer switches have been 3 cycle withstand current tested in accordance with UL 1008 & CSA 178. Additionally they can withstand 6 times overload for 10 cycles. The standard TS 870 Automatic Transfer Switch is rated for 100% system load. The TS 870 design allows optional use of integral over current trip elements within the power switching units. All TS 870 series transfer switches use a TSC 900 microprocessor based controller which provides all necessary control functions for fully automatic operation. The controller is equipped with 7" color touch-screen graphical display which provides Operating Status and controls. All parameters and configurations are entered without opening the front door.

SERVICE ENTRANCE ATS (For U.S. Market Only)

Thomson Power Systems TS 870 Service Entrance (SE) Automatic Transfer Switches incorporate an isolating mechanism and over current protection on the utility supply thereby removing the need to have a separate, upstream circuit breaker/disconnect switch. This unique Service Entrance Rated Automatic Transfer Switch design is incorporated into a standard sized automatic transfer switch enclosure.

Standard features of the Service Entrance Rated Automatic Transfer Switch include a NEMA 1 rated enclosure, pad-lockable Service Disconnect control switch and status indications.

TS 870 SE Service disconnect operation ensures a high level of safety for system maintenance personnel. Normal operation and performance of the automatic transfer switch is unaffected by the Service Entrance ATS feature. The TS 870 SE Automatic Transfer Switch is rated for the system load and requires upstream over current protection on the generator supply.

The TS 870 SE series transfer switches use a type TSC 900 microprocessor based controller.

WITHSTAND CURRENT RATINGS (ALL MODELS)

MODEL	RATED CURRENT (AMPS)	MAX VOLTAGE	WITHSTAND CURRENT RATING AMPS (RMS) ¹		
			@240V	@480V	@600V
TS 87XA - 0100	100A	600	65,000	25,000	18,000
TS 87XA - 0150	150A	600	65,000	25,000	18,000
TS 87XA - 0200	200A	240	65,000	N/A	N/A
TS 87XA - 0250	250A	600	65,000	65,000	35,000
TS 87XA - 0400	400A	600	65,000	50,000	35,000
TS 87XA - 0600	600A	600	65,000	50,000	35,000
TS 87XA - 0800	800A	600	65,000	50,000	35,000
TS 87XA - 1000	1000A	600	200,000	100,000	65,000
TS 87XA - 1200	1200A	600	200,000	100,000	65,000

¹ Note: For power switching devices equipped with optional overcurrent trip units, standard interrupting ratings are identical to withstand ratings shown at 240V and 480V. For interrupting ratings at 600V, contact Thomson Power Systems.

ENCLOSURE DIMENSIONS/CABLE TERMINALS (NEMA 1, ASA #61 GRAY)

AMPERAGE	NUMBER OF POLES	DIMENSIONS INCHES (mm) ¹			SHIPPING WEIGHT lbs (kg)	TERMINAL RATING ³	
		HEIGHT	WIDTH	DEPTH		QTY (PER PHASE)	RANGE
100A	2, 3, 4	31.1" (790)	22.3" (566)	14" (356)	143 lbs (65)	1	#14 - 1/0
150A	2, 3, 4	31.1" (790)	22.3" (566)	14" (356)	143 lbs (65)	1	#2 - 4/0
200A	2, 3, 4	31.1" (790)	22.3" (566)	14" (356)	143 lbs (65)	1	#6 - 350 mcm
250A	2, 3, 4	35.1" (892)	27.3" (693)	14" (356)	172 lbs (78)	1	#6 - 350 mcm
400A	2, 3	43.1" (1095)	34.3" (871)	13" (330)	227 lbs (103)	2	2/0 - 500 mcm
400A	4	48.1" (1222)	37.8" (960)	14.5" (368)	256 lbs (116)	2	2/0 - 500 mcm
600A	2, 3	46.1" (1171)	36.3" (922)	14.5" (368)	248 lbs (113)	2	2/0 - 500 mcm
600A	4	48.1" (1222)	37.8" (960)	14.5" (368)	256 lbs (116)	2	2/0 - 500 mcm
800A	2, 3	48.1" (1222)	37.8" (960)	14.5" (368)	309 lbs (140.4)	3	2/0 - 500 mcm
800A	4	63.1" (1603)	40.8" (1036)	14.5" (368)	367 lbs (167)	3	2/0 - 500 mcm
400A - 800A CTTS	2,3,4	64" (1626)	30" (762)	14" (356)	400 lbs (181)	3	2/0 - 500 mcm
1000A/1200A (All)	2, 3, 4	70" (1780)	34.3" (871)	14" (356)	550 lbs (249)	4	4/0 - 500 mcm

Optional NEMA 3R & 4X class enclosures available — consult Thomson Power Systems.

For ATS with Distribution Breaker Option contact factory for dimensions.

¹ Enclosure dimensions are for reference. (DO NOT USE FOR CONSTRUCTION)

³ All cable connections suitable for copper or aluminum

⁴ Optional terminal ratings are available in some models – Consult Thomson Power Systems



STANDARD FEATURES (With TSC 900 Controller)

- 7" color touch screen graphical display for monitoring 3 Phase Utility/Generator voltage, system frequency and timer countdown operation
- Front Panel Programming using touchscreen graphical display with password security
- Load on Utility & Load on Generator indication
- Utility & Generator Source available indication
- 3 Phase Voltage sensing on Utility & Generator Sources
- Generator AC frequency sensing
- Utility under voltage control setpoint 70 - 95% (adjustable)
- Generator under voltage control setpoint 70 - 95% (adjustable)
- Generator under frequency control setpoint 70 - 90% (adjustable)
- Engine warm-up timer 0-60 min. (adjustable)
- Utility return timer 0-60 min. (adjustable)
- Engine start timer 0-60 sec. (adjustable)
- Engine cooldown timer 0-60 min. (adjustable)
- Neutral position delay timer 0-120 sec. (adjustable)
- Load Disconnect Contact (LDC) for pre/post transfer control to signal external building systems such as elevators during transfer operations
- Programmable Generator Exercise Timer (EXT) with easy to use event, Calendar Based, On-load or Off-load Programmability
- Real-time clock c/w battery back-up & daylight-savings programming
- Data logging including total transfers to generator, total utility power failures, load on utility hours, load on generator hours and utility or generator voltage/frequency data at time of fault
- Eight user Programmable Output Contacts rated 2A, 120/240V resistive, Form C. Each output contact is user programmable to 20 different functions including: Load on Utility, Load on Gen, Load Disconnect Contact (LDC), Fail to Transfer (FTT), Utility Power Available (UPA), Generator Power Available (GPA), Utility Power Fail, Engine start, ATS Not in Auto, and ATS in Auto. The Transfer Switch is pre-programmed with the following outputs enabled:
 - Load on Utility
 - Load on Gen
 - Load Disconnect Contact (LDC)
 - Fail to Transfer (FTT)
 - ATS Not in Auto
- Local utility power fail simulation test
- Remote utility power fail simulation test pushbutton input
- Local plant exercise initiate pushbutton control
- Engine start contact (7A, 120/240VAC resistive max.)
- Transfer fail/forced transfer logic
- Automatic force transfer to alternate supply should load voltage become de-energized
- 50 or 60Hz capable (115V control power)
- Remote Load Test/Peak Shave Input
- NEMA 1 Enclosure
- Solid Neutral on 4 wire Systems
- Auto Configuring System Voltage Type (3 wire delta or 4 wire Wye capable without additional sensing transformers)
- ATS Load Bus Power Metering Capability (Amp, Volt, Freq, kW, kVA, PF). Requires Current Transformer Option Kit
- Under/Over Frequency Protection- Utility and Generator Sources
- 3 Phase Over Voltage Protection - Utility and Generator Sources
- Phase Sequence and Phase Rotation Protection between Utility and Generator Sources
- Voltage Phase Loss/Unbalance Protection
- Programmable Inputs (Quantity 16 Digital Input-voltage free input)
- RS232 Modbus™ Remote Communication Port (Modbus™ Serial RTU) via GHC
- Optional Ethernet Modbus Remote Communication Port (Modbus™ TCP) via GHC
- USB Communication Port (Quantity 3 via GHC)
- Serviceable Plug-in Connectors
- Event Logging (Time/Date Stamping)



ORDERING INFORMATION

When placing an order, specify the following 21 digit ATS MODEL CODE as per the features and applications described below.

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
T	S		8	7																

1-3. SERIES

TS - TRANSFER SWITCH

4 & 5. MODEL

87 - 870 SWITCH

6. POLES

2 - 2 POLE
3 - 3 POLE
4 - 4 POLE

7. CONFIGURATION TYPE

A - ATS
X - SPECIAL

8 - 11. AMPERAGE

0100
0150
0200⁵
0250
0400
0600
0800
1000
1200

12. APPLICATION

A - STANDARD
B - SERVICE ENTRANCE
C - DUAL UTILITY CONTROL
D - DUAL STANDBY GEN (Slave ATS)
H - DUAL PRIME GEN CONTROL
X - SPECIAL

13. OPERATION TYPE

1 - OPEN TRANSITION
2 - MANUAL ELEC. OP.
3 - CLOSED TRANSITION (MOMENTARY) ⁷
X - SPECIAL

14. SAFETY STANDARDS

A - UL 1008 (Service Entrance)
B - CSA C22.2 NO 178
C - UL 1008 / CSA 178
X - NOT APPLICABLE

15. VOLTAGE

1Ø 3 WIRE
D - 120/240

3Ø 4 WIRE (GROUNDED NEUTRAL)

E - 120/208 ¹
F - 127/220
G - 120/240 ¹ (DELTA)
H - 220/380 ²
S - 230/400 ²
J - 240/416
K - 254/440
M - 277/480 ¹
N - 347/600 ¹
Y - MULTIVOLTAGE (STOCK SWITCHES ONLY)
Customer to specify voltage when ordering

3Ø 3 WIRE

P - 208
Q - 220
R - 240
U - 416
V - 480
W - 600
X - SPECIAL

16. CONTROLLER

5 - TSC 900 c/w GHC Graphic Display
7 - NONE (MANUAL)

17. ENCLOSURE TYPE

A - NEMA 1, ASA #61 GRAY
B - NEMA 2, ASA #61 GRAY
C - NEMA 12, ASA #61 GRAY
D - NEMA 3R SD, ASA #61 GRAY
E - NEMA 3R DD, ASA #61 GRAY
F - NEMA 3RX/4X DD
(304 STAINLESS STEEL) ³
G - NONE (OPEN STYLE)
L - NEMA 3RX/4X DD
(316 STAINLESS STEEL) ³
X - SPECIAL

18. UTILITY SWITCHING DEVICE

K - MOLDED CASE SWITCH (100 - 1200A)
M - MOLDED CASE SWITCH C/W THER-MAG
TRIP (100-200A)
N - MOLDED CASE SWITCH C/W ELECTRONIC
TRIP (250-1200A)
P - MOLDED CASE SWITCH C/W ELECTRONIC
& GF TRIP (250-1200A)

19. GENERATOR SWITCHING DEVICE

K - MOLDED CASE SWITCH (100 - 1200A)
M - MOLDED CASE SWITCH C/W THER-MAG
TRIP (100-200A)
N - MOLDED CASE SWITCH C/W ELECTRONIC
TRIP (250-1200A)
P - MOLDED CASE SWITCH C/W ELECTRONIC
& GF TRIP (250-1200A)

20. POWER CONNECTIONS

A - STANDARD
B - ATS CONNECTION PLATE 100A-400A
C - ATS CONNECTION PLATE 600A-800A
D - ATS CONNECTION PLATE 1000A-1200A
E - ATS CONNECTION PLATE 100A-400A FOR U&G
F - ATS CONNECTION PLATE 600A-800A FOR U&G
G - ATS CONNECTION PLATE 1000A-1200A FOR U&G
X - SPECIAL

21. ATS CONNECTION CONFIGURATION

A - STANDARD
B - ALTERNATE B (400-1200A)
C - ALTERNATE C (400-1200A)
D - ALTERNATE D (400-1200A)

NOTES

¹ MULTI-VOLTAGE CAPABLE
² FOR 50 Hz APPLICATION
³ STANDARD ENCLOSURE RATING IS N3RX
AT 800A, N4X FOR 1000/1200A
AND 600A AND BELOW
⁵ 240V MAX
⁷ CLOSED TRANSITION OPTION 400A - 1200A ONLY

AVAILABLE IN STOCK

The following standard ATS models are available from stock:

AMPERAGE	3 POLE	2 POLE OPTION TS 872	SERVICE ENTRANCE RATED ATS	SOLID NEUTRAL	MULTI- VOLTAGE (CUSTOMER TO SPECIFY 208-600V)	TSC 900 CONTROLLER	NEMA 1 ENCLOSURE	NEMA 3R ENCLOSURE OPTIONS	8 PROGRAMMABLE OUTPUT CONTACTS (2A, 240VAC)	MODBUS™ RTU REMOTE COMMU- NICATION PORT (SERIAL RS 232)
100A	Standard	Available Option in Stock		Standard		Standard	Standard	Available Option in Stock	Standard	Standard
150A	Standard	Available Option in Stock		Standard		Standard	Standard	Available Option in Stock	Standard	Standard
200A	Standard	Available Option in Stock	Available Option in Stock	Standard	240V Max	Standard	Standard	Available Option in Stock	Standard	Standard
250A	Standard	Available Option in Stock	Available Option in Stock	Standard		Standard	Standard	Available Option in Stock	Standard	Standard
400A	Standard	Available Option in Stock	Available Option in Stock	Standard		Standard	Standard	Available Option in Stock	Standard	Standard
600A	Standard	Available Option in Stock	Available Option in Stock	Standard		Standard	Standard	Available Option in Stock	Standard	Standard
800A	Standard	Available Option in Stock	Available Option in Stock	Standard		Standard	Standard	Available Option in Stock	Standard	Standard

Standard
Available Option in Stock



OPTIONAL FEATURES (Specify separately from ATS MODEL CODE when ordering)

CODE

DESCRIPTION

AUXILIARIES:

AUX-BG	Generator Bypass Auxiliary Contact
AUX-BU	Utility Bypass Auxiliary Contact
KOTS	Key Operated Test Switch- Auto/Off/Engine Start/Test
PPR-10	Programmable Power Relay Includes 10A Form C Contact Wired to Terminal Block (Up to Qty 3). Requires 24VDC External Control Power
TS-STG	24Vdc or 120VAC Shunt Trip Generator Switch (external power source required)
TS-STU	24Vdc or 120VAC Shunt Trip Utility Switch (external power source required)

COMMUNICATION:

EMB-TCP/IP	Ethernet Modbus™ Remote Communication Port (Modbus™ TCP) via GHC
RS485A	RS 232 to RS 485 Remote Communication Adapter
WF-USB	WIFI USB Stick
THS 900	Remote Communication Application- Windows Based
RA 900	* Requires EMB-TCP/IP Option

ENCLOSURE:

GHC-SS	Sunshade for GHC Screen
LCK	Enclosure Lockable Door (Single point T-Handle lock)
TS-H1	Enclosure Strip Heater c/w Thermostat (120VAC external power source required)
TS-H2	Enclosure Strip Heater c/w Thermostat (internally powered from ATS load)

FUNCTION:

DU	Dual Utility Control Package
DSG	Dual Standby Generator Control Package (Slave ATS). Requires 24DCC Option to Power TSC 900
DPG	Dual Prime Generator Control Package.
MTS	Manually Initiated Electrically Operated Transfer Switch c/w Source Selector Switch, Position Indicating Lights, Source Available Lights
TCP	Transfer Switch Connection Plate for Generator Supply
TS-SS	Internal Multi-Voltage Selector Switch (208V/240V/480V)

METERING:

LPM	Transfer Switch Load Power Metering CT Kit (Amp, Volt, Freq, kW, kVA, PF) **Requires CT Kit
CTKxxxx	Current Transformer Kit (xxxx -Specify CT Size 0100, 0150, 0250, 0400, 0600, 0800, 1200)
MUP	Multifunction Utility Protective Relay – Basler IPS100 (Protection Functions 27, 32, 47, 50/51, 67, 81O/U (Note: May be required by local utility for Momentary CT applications. Consult factory for other makes and models.)

POWER:

24DCC	24 Volt DC-DC Converter, Regulated
SPD	Surge Protection Device

OTHER:

3YR	Additional 12 Month Parts & Labour Warranty
5YR	Additional 48 Month Parts & Labour Warranty



Thomson Power Systems

9087A - 198th Street
Langley, BC, Canada V1M 3B1
Customer Service: 604-888-0110
info@thomsonps.com
www.thomsonps.com



NOTE: Specifications subject to change without notice.

APPLICATION CONSIDERATIONS

The proper selection and application of power generation products and components, including the related area of product safety, is the responsibility of the customer. Operating and performance requirements and potential associated issues will vary appreciably depending upon the use and application of such products and components. The scope of the technical and application information included in this publication is necessarily limited. Unusual operating environments and conditions, and other factors can materially affect the application and operating results of the products and components and the customer should carefully review its requirements. Any technical advice or review furnished by Regal Beloit America, Inc. and its affiliates with respect to the use of products and components is given in good faith and without charge, and Regal assumes no obligation or liability for the advice given, or results obtained, all such advice and review being given and accepted at customer's risk.

For a copy of our Standard Terms and Conditions of Sale, Disclaimers of Warranty, Limitation of Liability and Remedy, please contact Customer Service at 1-888-888-0110. These terms and conditions of sale, disclaimers and limitations of liability apply to any person who may buy, acquire or use a Regal Beloit America Inc. product referred to herein, including any person who buys from a licensed distributor of these branded products.

Thomson Power Systems and Regal are trademarks of Regal Beloit Corporation or one of its affiliated companies.

©2016, 2017 Regal Beloit Corporation, All Rights Reserved. CL062r11 17/04/24

